

(19)



Europäisches Patentamt

European Patent Office

Office européen des brevets



(11)

EP 1 073 212 A2

(12)

EUROPEAN PATENT APPLICATION

(43) Date of publication:

31.01.2001 Bulletin 2001/05

(51) Int Cl.7: H04B 7/005, H04B 7/06

(21) Application number: 00304512.7

(22) Date of filing: 26.05.2000

(84) Designated Contracting States:

AT BE CH CY DE DK ES FI FR GB GR IE IT LI LU
MC NL PT SE

Designated Extension States:

AL LT LV MK RO SI

(30) Priority: 28.05.1999 US 136413 P

(71) Applicant: Texas Instruments Incorporated
Dallas, Texas 75251 (US)

(72) Inventors:

- Dabak, Anand G.
Plano, Texas 75025 (US)
- Hosur, Srinath
Plano, Texas 75025 (US)

(74) Representative:

Legg, Cyrus James Grahame et al
ABEL & IMRAY,
20 Red Lion Street
London WC1R 4PQ (GB)

(54) **Wireless system with transmitter with multiple antennas and combining open loop and closed loop transmit diversity**

(57) A wireless communication system (40). The system comprises transmitter circuitry (42) comprising encoder circuitry (44) for receiving a plurality of symbols (S_i). The system further comprises a plurality of antennas (AT1-AT4) coupled to the transmitter circuitry and

for transmitting signals from the transmitter circuitry to a receiver (UST), wherein the signals are responsive to the plurality of symbols. Further, the encoder circuitry is for applying open loop diversity and closed loop diversity to the plurality of symbols to form the signals.




FIG. 4

Description

CROSS-REFERENCES TO RELATED APPLICATIONS

- 5 [0001] This application claims the benefit, under 35 U.S.C. §119(e)(1), of U.S. Provisional Application No. 60/136,413 (TI-29286PS), filed May 28, 1999, and incorporated herein by this reference.

STATEMENT REGARDING FEDERALLY SPONSORED RESEARCH OR DEVELOPMENT

- 10 [0002] Not Applicable.

BACKGROUND OF THE INVENTION

- 15 [0003] The present embodiments relate to wireless communications systems and, more particularly, to transmitters with multiple transmit antennas used in such systems.

- [0004] Wireless communications have become very prevalent in business, personal, and other applications, and as a result the technology for such communications continues to advance in various areas. One such advancement includes the use of spread spectrum communications, including that of code division multiple access ("CDMA") and wideband code division multiple access ("WCDMA") cellular communications. In such communications, a user station (e.g., a hand held cellular phone) communicates with a base station, where typically the base station corresponds to a "cell."

- [0005] Due to various factors including the fact that CDMA communications are along a wireless medium, an originally transmitted communication from a base station to a user station may arrive at the user station at multiple and different times. Each different arriving signal that is based on the same original communication is said to have a diversity with respect to other arriving signals originating from the same transmitted communication. Further, various diversity types may occur in CDMA communications, and the CDMA art strives to ultimately receive and process the originally transmitted data by exploiting the effects on each signal that are caused by the one or more diversities affecting the signal.

- [0006] One type of CDMA diversity occurs because a transmitted signal from the base station is reflected by objects such as the ground, mountains, buildings, and other things that it contacts. As a result, a same single transmitted communication may arrive at the receiver at numerous different times, and assuming that each such arrival is sufficiently separated in time, then each different arriving signal is said to travel along a different channel and arrive as a different "path." These multiple signals are referred to in the art as multiple paths or multipaths. Several multipaths may eventually arrive at the user station and the channel traveled by each may cause each path to have a different phase, amplitude, and signal-to-noise ratio ("SNR"). Accordingly, for one communication between one base station and one user station, each multipath is a replica of the same user information, and each path is said to have time diversity relative to other multipath(s) due to the difference in arrival time which causes different (uncorrelated) fading/noise characteristics for each multipath. Although multipaths carry the same user information to the receiver, they may be separately recognized by the receiver based on the timing of arrival of each multipath. More particularly, CDMA communications are modulated using a spreading code which consists of a series of binary pulses, and this code runs at a higher rate than the symbol data rate and determines the actual transmission bandwidth. In the current industry, each piece of CDMA signal transmitted according to this code is said to be a "chip," where each chip corresponds to an element in the CDMA code. Thus, the chip frequency defines the rate of the CDMA code. Given the use of transmission of the CDMA signal using chips, then multipaths separated in time by more than one of these chips are distinguishable at the receiver because of the low auto-correlations of CDMA codes as known in the art.

- [0007] In contrast to multipath diversity which is a natural phenomenon, other types of diversity are sometimes designed into CDMA systems in an effort to improve SNR, thereby improving other data accuracy measures (e.g., bit error rate ("BER"), frame error rate ("FER"), and symbol error rate ("SER")). An example of such a designed diversity scheme is antenna diversity and is introduced here since it has particular application to the preferred embodiments discussed later. Antenna diversity, or sometimes referred to as antenna array diversity, describes a wireless system using more than one antenna by a same station. Antenna diversity often proves useful because fading is independent across different antennas. Further, the notion of a station using multiple antennas is more typically associated with a base station using multiple antennas to receive signals transmitted from a single-antenna mobile station, although more recently systems have been proposed for a base station using multiple antennas to transmit signals transmitted to a single-antenna mobile station. Each of these alternatives is further explored below.

- 55 [0008] Certain antenna array diversity techniques suggest the use of more than one antenna at the receiver, and this approach is termed receive antenna diversity. For example, in prior art analog systems, often a base station receiver was equipped with two antennas, each for receiving a signal from a single-antenna mobile station. Thus, when the single-antenna mobile station transmits to the base station, each receiver antenna provides at least one corresponding

received signal for processing. By implementing multiple receive antennas, the performance of an ideal receiver is enhanced because each corresponding received signal may be separately processed and combined for greater data accuracy.

[0009] More recently there have been proposals to use more than one antenna at the transmitter, and this approach is termed transmit antenna diversity. For example, in the field of mobile communications, a base station transmitter is equipped with two antennas for transmitting to a single-antenna mobile station. The use of multiple antennas at the base station for transmitting has been viewed as favorable over using multiple antennas at the mobile station because typically the mobile station is in the form of a hand-held or comparable device, and it is desirable for such a device to have lower power and processing requirements as compared to those at the base station. Thus, the reduced resources of the mobile station are less supportive of multiple antennas, whereas the relatively high-powered base station more readily lends itself to antenna diversity. In any event, transmit antenna diversity also provides a form of diversity from which SNR may be improved over single antenna communications by separately processing and combining the diverse signals for greater data accuracy at the receiver. Also in connection with transmit antenna diversity and to further contrast it with multipath diversity described above, note that the multiple transmit antennas at a single station are typically within several meters (e.g., three to four meters) of one another, and this spatial relationship is also sometimes referred to as providing spatial diversity. Given the spatial diversity distance, the same signal transmitted by each antenna will arrive at a destination (assuming no other diversity) at respective times that relate to the distance between the transmitting antennas. However, the difference between these times is considerably smaller than the width of a chip and, thus, the arriving signals are not separately distinguishable in the same manner as are multipaths described above.

[0010] Given the development of transmit antenna diversity schemes, two types of signal communication techniques have evolved to improve data recognition at the receiver given the transmit antenna diversity, namely, closed loop transmit diversity and open loop transmit diversity. Both closed loop transmit diversity and open loop transmit diversity have been implemented in various forms, but in all events the difference between the two schemes may be stated with respect to feedback. Specifically, a closed loop transmit diversity system includes a feedback communication channel while an open loop transmit diversity system does not. Both of these systems as well as the distinction between them are further detailed below.

[0011] Figure 1 illustrates a prior art closed loop transmit antenna diversity system 10 including a transmitter 12 and a receiver 14. By way of example, assume that transmitter 12 is a base station while receiver 14 is a mobile station. Also, for the sake of simplifying the discussion, each of these components is discussed separately below. Lastly, note that the closed loop technique implemented by system 10 is sometimes referred to in the art as a transmit adaptive array ("TxAA"), while other closed loop techniques also should be ascertainable by one skilled in the art.

[0012] Transmitter 12 receives information bits B_i at an input to a channel encoder 14. Channel encoder 14 encodes the information bits B_i in an effort to improve raw bit error rate. Various encoding techniques may be used by channel encoder 14 and as applied to bits B_i with examples including the use of convolutional code, block code, turbo code, or a combination of any of these codes. The encoded output of channel encoder 14 is coupled to the input of an interleaver 15. Interleaver 15 operates with respect to a block of encoded bits and shuffles the ordering of those bits so that the combination of this operation with the encoding by channel encoder 14 exploits the time diversity of the information. For example, one shuffling technique that may be performed by interleaver 15 is to receive bits in a matrix fashion such that bits are received into a matrix in a row-by-row fashion, and then those bits are output from the matrix to a symbol mapper 16 in a column-by-column fashion. Symbol mapper 16 then converts its input bits to symbols, designated generally as S_j . The converted symbols S_j may take various forms, such as quadrature phase shift keying ("QPSK") symbols, binary phase shift keying ("BPSK") symbols, or quadrature amplitude modulation ("QAM") symbols. In any event, symbols S_j may represent various information such as user data symbols, as well as pilot symbols and control symbols such as transmit power control ("TPC") symbols and rate information ("RI") symbols. Symbols S_j are coupled to a modulator 18. Modulator 18 modulates each data symbol by combining it with, or multiplying it times, a CDMA spreading sequence which can be a pseudo-noise ("PN") digital signal or PN code or other spreading codes (i.e., it utilizes spread spectrum technology). In any event, the spreading sequence facilitates simultaneous transmission of information over a common channel by assigning each of the transmitted signals a unique code during transmission. Further, this unique code makes the simultaneously transmitted signals over the same bandwidth distinguishable at receiver 14 (or other receivers). Modulator 18 has two outputs, a first output 18₁ connected to a multiplier 20₁ and a second output 18₂ connected to a multiplier 20₂. Each of multipliers 20₁ and 20₂ multiplies its input times a weight value, W_1 and W_2 , respectively, and provides an output to a respective transmit antenna A12₁ and A12₂. By way of example, assume that transmit antennas A12₁ and A12₂ are approximately three to four meters apart from one another.

[0013] Receiver 14 includes a receive antenna A14, for receiving communications from both of transmit antennas A12₁ and A12₂. Recall that such communications may pass by various multipaths, and due to the spatial relationship of transmit antennas A12₁ and A12₂, each multipath may include a communication from both transmit antenna A12₁

and transmit antenna A12₂. In the illustration of Figure 1, a total of j multipaths are shown. Further, each multipath will have a fading channel parameter associated with it, that is, some value that reflects the channel effects on the signal carried by the channel. By way of reference, the character α is used in this document to identify this fading parameter; moreover, in Figure 1, the convention α_i^j is used, where $i=1$ identifies a path transmitted by the antenna A12₁, $i=2$ identifies a path transmitted by the antenna A12₂, and j identifies the multipath. Within receiver 14, signals received by antenna A14₁ are connected to a despreader 22. Despreader 22 operates according to known principles, such as by multiplying the CDMA signal times the CDMA code for receiver 14, thereby producing a despread symbol stream at its output and at the symbol rate. The despread signals output by despreader 22 are coupled to an open loop diversity decoder 23, and also to a channel estimator 24. Channel estimator 24 determines estimated channel impulse responses based on the incoming despread data. Further, channel estimator 24 provides two outputs. A first output 24₁ from channel estimator 24 outputs the estimated channel impulse responses to open loop diversity decoder 23. In response to receiving the estimates, open loop diversity decoder 23 applies the estimates to the despread data received from despreader 22; further in this regard and although not separately shown, the application of the estimate to the data may be by way of various methods, such as maximal ratio combining (MRC) and using a rake receiver. A second output 24₂ from channel estimator 24 communicates the estimates, or values derived from those estimates, back to transmitter 12 via a feedback channel. These feedback values are the weights W_1 and W_2 described above with respect to multipliers 20₁ and 20₂ of transmitter 12.

[0014] Returning to open loop diversity decoder 23 of receiver 14, once it applies the estimates to the despread data, its result is output to a deinterleaver 25 which operates to perform an inverse of the function of interleaver 15, and the output of deinterleaver 25 is connected to a channel decoder 26. Channel decoder 26 may include a Viterbi decoder, a turbo decoder, a block decoder (e.g., Reed-Solomon decoding), or still other appropriate decoding schemes as known in the art. In any event, channel decoder 26 further decodes the data received at its input, typically operating with respect to certain error correcting codes, and it outputs a resulting stream of decoded symbols. Indeed, note that the probability of error for data input to channel decoder 26 is far greater than that after processing and output by channel decoder 26. For example, under current standards, the probability of error in the output of channel decoder 26 may be between 10^{-3} and 10^{-6} . Finally, the decoded symbol stream output by channel decoder 26 may be received and processed by additional circuitry in receiver 14, although such circuitry is not shown in Figure 1 so as to simplify the present illustration and discussion.

[0015] Having detailed system 10, attention is now returned to its identification as a closed loop system. Specifically, system 10 is named a closed loop system because, in addition to the data communication channels from transmitter 12 to receiver 14, system 10 includes the feedback communication channel for communicating weights W_1 and W_2 from receiver 14 to transmitter 12; thus, the data communication and feedback communication channels create a circular and, hence, "closed" loop system. Note further that weights W_1 and W_2 may reflect various channel affecting aspects. For example, receiver 14 may ascertain a level of fading in signals it receives from transmitter 12, such as may be caused by local interference and other causes such as the Doppler rate of receiver 14 (as a mobile station), and in any event where the fading may be characterized by Rayleigh fading. As a result, receiver 14 feeds back weights W_1 and W_2 and these weights are used by multipliers 20₁ and 20₂, thereby applying weight W_1 to various symbols to provide a transmitted signal along transmitter antenna A12₁ and applying weight W_2 to various symbols to provide a transmitted signal along transmitter antenna A12₂. Thus, for a first symbol S_1 to be transmitted by station 12, it is transmitted as part of a product $W_1 S_1$ along transmitter antenna A12₁ and also as part of a product $W_2 S_1$ along transmitter antenna A12₂. By way of illustration, therefore, these weighted products are also shown in Figure 1 along their respective antennas.

[0016] Turning now to a prior art open loop transmit diversity system, it may be described generally and in comparison to the closed loop system 10 of Figure 1, where the primary distinction is that the prior art open loop transmit diversity system does not require feedback. Thus, to depict an open loop system the illustration of Figure 1 may be modified by removing the feedback channel, weights W_1 and W_2 , and multipliers 20₁ and 20₂, with the remaining blocks thereby generally illustrating an open loop transmit diversity system. Given that the open loop transmit diversity system does not include feedback, it instead employs an alternative technique to adjust data differently for each of its transmit antennas. Therefore, the open loop system receiver then attempts to properly evaluate the data in view of the known transmitter adjustment. Thus, the processing and algorithms implemented within the receiver decoder of an open loop system will differ from those in a closed loop system.

[0017] To further depict open loop transmit diversity, Figure 2 illustrates, by way of example, a prior art open loop transmitter 30 that is referred to as providing space time block coded transmit antenna diversity ("STTD"), and further in this regard transmitter 30 includes an STTD encoder 32. STTD encoder 32 has an input 34, which by way of example is shown to receive a first symbol S_1 at a time T followed by a second symbol S_2 at a time $2T$. For the sake of the present example, assume that symbols S_1 and S_2 are QPSK symbols. STTD encoder 32 has two outputs 36₁ and 36₂, each connected to a respective antenna A32₁ and A32₂.

[0018] The operation of transmitter 30 is now explored, and recall in general from above that open loop system

transmitters adjust data differently at each transmit antenna without the assistance of feedback. In the case of transmitter 30, STTD encoder 32 first buffers a number of symbols equal to the number of transmit antennas. In the example of Figure 2 which has two transmit antennas A32₁ and A32₂, STTD encoder 32 therefore buffers two symbols (e.g., S₁ and S₂). Next, STTD encoder 32 directly transmits the buffered symbols along antenna A32₁ and, thus, in Figure 2 symbol S₁ is transmitted at a time T' and symbol S₂ is transmitted at a time 2T'. During the same time, however, and for transmission along antenna A32₂, the complex conjugates of the symbols are formed and reversed in order. For the example of Figure 2, therefore, these two operations create, in the reversed order, a sequence of S₂^{*} and S₁^{*}. Moreover, when transmitted along antenna A32₂, the negative value of the first of these two symbols is transmitted while the positive value of the second symbol is transmitted. Accordingly, in Figure 2 and with respect to antenna A32₂, a symbol -S₂ is transmitted at a time T' and a symbol S₁^{*} is transmitted at a time 2T'. From the symbols transmitted by STTD encoder 32, a compatible receiver is therefore able to resolve the symbols in a manner that often yields favorable data error rates even given relatively large Doppler rates. Finally, note also by way of an alternative example that if symbols S₁ and S₂ were BPSK symbols, then such symbols would include only real components (i.e., they do not include a complex component). In this case, along antenna A32₁ system 30 would transmit symbol S₁ at time T' and symbol S₂ at time 2T', while along antenna A32₂ system 30 would transmit symbol S₂ at time T' and symbol -S₁ at time 2T'.

[0019] Having detailed both closed loop and open loop transmit antenna diversity systems, additional observations are now made regarding the benefits and drawbacks of each. In general, under the ideal situation, a closed loop system outperforms an open loop system for a given transmitted signal power. However, due to non-ideal occurrences in the feedback information, a closed loop system may be inferior to an open loop system in some situations. For example, as Doppler fading increases, by the time the feedback information is received by the transmitter, the weights included or derived from the feedback information may be relatively outdated and therefore less effective when applied to future transmissions by the transmitter. Conversely, because the open loop system does not implement feedback from the receiver to the transmitter, then such a system may provide greater performance in a high Doppler environment. In the prior art, the drawbacks of both the closed loop and open loop systems have been addressed in one manner by further increasing the number of antennas in either the closed loop or open loop system. While this approach may improve error rates as compared to fewer antennas for the same system, there are diminishing returns in data error rates to be considered versus the complexities of adding more antennas to a system. Moreover, for each antenna added to a closed loop diversity system, there is a corresponding increase in the amount of bandwidth required to accommodate the additional feedback information required for the added transmit antenna.

[0020] An object of the present invention is to improve on prior art systems and is met by the embodiments described below.

BRIEF SUMMARY OF THE INVENTION

[0021] In the preferred embodiment, there is a wireless communication system. The system comprises transmitter circuitry comprising encoder circuitry for receiving a plurality of symbols. The system further comprises a plurality of antennas coupled to the transmitter circuitry and for transmitting signals from the transmitter circuitry to a receiver, wherein the signals are responsive to the plurality of symbols. Further, the encoder circuitry is for applying open loop diversity and closed loop diversity to the plurality of symbols to form the signals. Other circuits, systems, and methods are also disclosed and claimed.

BRIEF DESCRIPTION OF THE SEVERAL VIEWS OF THE DRAWING

[0022] Figure 1 illustrates an electrical diagram of a prior art closed loop transmit antenna diversity system.

[0023] Figure 2 illustrates an electrical diagram of a transmitter in a prior art open loop transmit antenna diversity system.

[0024] Figure 3 illustrates a diagram of a cellular communications system by way of a contemporary example in which the preferred embodiments operate.

[0025] Figure 4 illustrates an electrical diagram of the preferred base station transmitter and mobile station receiver of Figure 3.

[0026] Figure 5 illustrates an open and closed loop encoder for transmitting along two antennas.

[0027] Figure 6 illustrates an OTD encoder for transmitting open loop diverse signals along four antennas.

[0028] Figure 7 illustrates a space time block coded transmit antenna diversity encoder for transmitting open loop diverse signals along four antennas.

[0029] Figure 8 illustrates a time switched time diversity encoder for transmitting open loop diverse signals along four antennas.

DETAILED DESCRIPTION OF THE INVENTION

[0030] Figures 1 and 2 were described above in the Background Of The Invention section of this document and the reader is assumed to be familiar with the details described in that section.

[0031] Figure 3 illustrates a diagram of a cellular communications system 40 by way of a contemporary example in which the preferred embodiments operate. Within system 40 is shown a base station BST, which includes four antennas AT1 through AT4 along which base station BST may transmit (or receive) CDMA or WCDMA signals. In the preferred embodiment, each antenna in the group of antennas AT1 through AT4 is within approximately three to four meters of another antenna in the group. In other embodiments, however, note that the multiple transmit antennas may be much closer to one another; for example, in an environment where base station BST and user station UST are both indoor stations, the distance between the multiple transmit antennas of base station BST may be on the order of inches. Returning to the example of Figure 1, the general area of intended reach of base station BST defines a corresponding CELL and, thus, base station BST is intended to generally communicate with other cellular devices within that CELL. Beyond the CELL there may other cells, each having its own corresponding base station, and indeed there may be some overlap between the illustrated CELL and one or more other cells adjacent the illustrated CELL. Such overlap is likely to support continuous communications should a mobile communication station move from one cell to another. Further in this regard, system 40 also includes a user station UST, which is shown in connection with a vehicle V to demonstrate that user station UST is mobile. By way of example, user station UST includes a single antenna ATU for both transmitting and receiving cellular communications.

[0032] In various respects, system 40 may operate according to known general techniques for various types of cellular or other spread spectrum communications, including CDMA or WCDMA communications. Such general techniques are known in the art and include the commencement of a call from user station UST and the handling of that call by base station BST. Where system 40 differs from the prior art, however, is the system for, and method of, communicating signals from each of the four antennas AT1 through AT4 to user station UST. These distinctions are further detailed below in connection with Figure 4.

[0033] Figure 4 illustrates an electrical block diagram of base station BST and user station UST from system 40 of Figure 3. For the sake of discussion, each of base station BST and user station UST is separately detailed below. By way of introduction, however, one skilled in the art will appreciate from the following details that system 40 presents a transmitter with more than two antennas (e.g., four in Figure 4), where its signals are communicated using a combination of open loop and closed loop communication techniques.

[0034] Looking to base station BST in Figure 4, it includes a transmitter 42 which further includes two separate STTD encoders 44 and 46, both of which receive the same stream of symbols. By way of example, two input symbols are shown, a symbol S_1 at a time T and a symbol S_2 and a time 2T. Symbols S_1 and S_2 may be provided by other circuitry (not shown) within base station BST that is either part of transmitter 42 or external from it, and such other circuitry may be appreciated by way of example with reference to the circuitry preceding modulator 18 in Figure 1. Returning to STTD encoder 44, it has outputs 44₁ and 44₂ connected to respective antennas AT1 and AT2. STTD encoder 46 has outputs 46₁ and 46₂ connected to respective antennas AT3 and AT4.

[0035] The operation of transmitter 42 is as follows. First, recall it is noted above that system 40 combines open loop and closed loop communication techniques. In the embodiment of Figure 4 and as now presented in detail, this combination is achieved by implementing an open loop communication technique per STTD encoder and by implementing a closed loop communication technique as between one STTD encoder versus another STTD encoder. As another manner of stating the combination and as further appreciated below, system 40 implements an open loop communication technique for a first and second pair of its transmit antennas, and it further implements a closed loop diversity communication technique as between the first transmit antenna pair relative to the second transmit antenna pair. Each of these different techniques, and their combination, is discussed below.

[0036] The open loop communication aspect of transmitter 42 may be appreciated by way of example with respect to STTD encoder 44, and note that the signals output by STTD encoder 44 to antennas AT1 and AT2 are shown in Figure 4; from these signals, it may be appreciated that all of the signals have a common factor of a weight, W_1 , which is further appreciated from the later discussion of the closed loop technique and which for the immediately following discussion is ignored so as to appreciate the open loop technique. Looking now to the factors other than the weight, W_1 , in the output signals of STTD encoder 44, one skilled in the art will appreciate that such signals alone represent an open loop diversity communication technique. Specifically, STTD encoder 44 first buffers a number of symbols equal to the number of transmit antennas to which it is connected, which is two antennas (i.e., AT1 and AT2) in the present example. Thus, STTD encoder 44 buffers symbols S_1 and S_2 . Next, STTD encoder 44 directly transmits the buffered symbols S_1 and S_2 along antenna AT1 and, thus, in Figure 4 symbol S_1 is transmitted at a time T' and symbol S_2 is transmitted at a time 2T'. During the same time, and for transmission along antenna AT2, the complex conjugate of the symbols are formed and reversed in order, and after the reversal the negative value of the first symbol conjugate is communicated (i.e., $-S_2^*$) at time T' followed by the positive value of the second symbol conjugate (i.e., S_1^*) at time

2T'. Given the preceding with respect to the pair of antennas AT1 and AT2, it should be appreciated that system 40 implements an open loop communication technique relative to that transmit antenna pair.

[0037] The open loop diversity communication technique of system 40 may be appreciated further with reference to the pair of transmit antennas AT3 and AT4 and STTD encoder 46 which outputs signals to those antennas. Looking to the signals output along antennas AT3 and AT4, they each have a common factor of a weight, W_2 . Looking to the factors other than the weight, W_2 , in the output signals of STTD encoder 46, such signals alone also represent an open loop diversity communication technique. Specifically, STTD encoder 46 also buffers symbols S_1 and S_2 and transmits them in the same manner as STTD encoder 44 described above. Thus, STTD encoder 46 directly transmits symbols S_1 and S_2 along antenna AT3 (at time T' and $2T'$, respectively) and STTD 46 encoder at the same time transmits $-S_2^*$, the negative symbol conjugate of the second symbol, at time T' followed by S_1^* , the positive symbol conjugate of the first symbol, at time $2T'$. These communications further demonstrate that system 40 implements an open loop communication technique relative to the pair of transmit antennas AT3 and AT4.

[0038] The closed loop diversity communication aspect of transmitter 42 may be appreciated by examining the differences in the output signals of STTD encoders 44 and 46, and further in view of user station UST. Looking first to user station UST, it includes a despreader 48, an open and closed loop diversity decoder 49, a channel estimator 50, a deinterleaver 51, and a channel decoder 52. Each of these devices may be constructed and operate according to techniques in various respects ascertainable by one skilled in the art and in view of the earlier discussion relative to Figure 1; further, however, recall that system 40 communicates signals using a combination of open loop and closed loop communication techniques. Thus, decoder 49 should be constructed to perform both open loop and closed loop diversity decoding, and preferably these operations should be simultaneous with respect to both diversity types since those diversity types are both combined into the signals received by receiver UST, as will be appreciated further in view of the combined open and closed loop transmit antenna diversity techniques described in this document. At the present point in this discussion, note that channel estimator 50 determines estimated channel impulse responses based on the incoming despread data as further detailed below, and in addition to providing the estimates to decoder 49 via an output 50_1 , it also provides via an output 50_2 the estimates, or values derived from those estimates, back to base station BST via a feedback channel. These feedback values are shown in Figure 4 as weights W_1 and W_2 and may be returned individually or as a ratio (e.g., W_2/W_1). Returning now to transmitter 42 of base station BST, its use of weights W_1 and W_2 to implement its closed loop aspect now may be appreciated. Specifically, weight W_1 is coupled to a multiplier 44_M associated with or as part of STTD encoder 44, and as a result weight W_1 is multiplied times each symbol to be output by STTD encoder 44. Accordingly, the factor of W_1 may be seen in Figure 4 in each of the output signals from STTD encoder 44 (i.e., as transmitted by antennas AT1 and AT2). Similarly, weight W_2 is coupled to a multiplier 46_M associated with or as part of STTD encoder 46, and as a result weight W_2 is multiplied times each symbol to be output by STTD encoder 46. Accordingly, the factor of W_2 may be seen in Figure 4 in each of the output signals from STTD encoder 46 (i.e., as transmitted by antennas AT3 and AT4). Thus, different weights are included within different output signals of base station BST and those weights are in response to the feedback channel from user station UST. Accordingly, the use of the different weights by system 40 demonstrates a closed loop communication technique as between one pair of transmit antennas (e.g., AT1 and AT2) relative to another pair of transmit antennas (e.g., AT3 and AT4).

[0039] Having demonstrated the use of weights W_1 and W_2 in the closed loop aspect of system 40, attention is now directed to the generation of the optimum value for those weights by channel estimator 50. Specifically, these weights are calculated as follows. First, the following Equation 1 defines a matrix, \overline{W} , for further generation of the weights W_1 and W_2 :

$$\overline{W} = \begin{bmatrix} W_1 \\ W_2 \end{bmatrix} \quad \text{Equation 1}$$

[0040] Next, the following Equations 2 and 3 define channel impulse response matrices for each of antennas AT1 through AT4 in system 40, where h_i is the channel impulse response matrix for antenna AT*i* in system 40.

$$H_1 = [h_1 \ h_3] \quad \text{Equation 2}$$

$$H_2 = [h_2 \ h_4] \quad \text{Equation 3}$$

[0041] For each of Equations 2 and 3, if there are a total of N resolvable multipaths from base station BST to user station UST, then h_i is further defined as a vector relating to each of those multipaths as shown in the following Equation 4:

$$h_i = \begin{bmatrix} \alpha_i^1 \\ \alpha_i^2 \\ \vdots \\ \alpha_i^N \end{bmatrix} \quad \text{Equation 4}$$

[0042] Next, a term r_1 is defined in Equation 5 and is the signal received by user station UST after despreading the signal transmitted over time $[0, T)$ and taking into account a noise factor, n_1 :

$$r_1 = h_1 W_1 S_1 - h_2 W_1 S_2 + h_3 W_2 S_1 - h_4 W_2 S_2 + n_1 \quad \text{Equation 5}$$

[0043] Similarly, a term r_2 is defined in Equation 6 and is the signal received by user station UST after despreading the signal transmitted over time $[T, 2T)$, and taking into account a noise factor, n_2 :

$$r_2 = h_1 W_1 S_2 + h_2 W_1 S_1 + h_3 W_2 S_2 + h_4 W_2 S_1 + n_2 \quad \text{Equation 6}$$

[0044] Rearranging the preceding yields Equation 7 for the value r_1 :

$$r_1 = (h_1 W_1 + h_3 W_2) S_1 - (h_2 W_1 + h_4 W_2) S_2 + n_1 = H_1 \bar{W} S_1 - H_2 \bar{W} S_2 + n_1 \quad \text{Equation 7}$$

[0045] Rearranging the preceding yields Equation 8 for the value r_2 :

$$r_2 = (h_2 W_1 + h_4 W_2) S_1 + (h_1 W_1 + h_3 W_2) S_2 + n_2 = H_2 \bar{W} S_1 + H_1 \bar{W} S_2 + n_2 \quad \text{Equation 8}$$

[0046] When signals r_1 and r_2 reach decoder 52, they are decoded as known in the STTD art. This decoding therefore may be represented as in the following Equation 9, and using the conventions that the symbol $(.)^H$ denotes conjugate transpose of a vector, the symbol $(.)^T$ denotes a transpose of a vector, and the symbol $(.)^*$ denotes its conjugate:

$$\begin{aligned} \bar{W}^H H_1^H r_1 + \bar{W}^T H_2^T r_2 = \\ (\bar{W}^H H_1^H H_1 \bar{W}) S_1 + (\bar{W}^T H_2^T H_2 \bar{W}^*) S_1 + \bar{W}^H H_1^H n_1 + \bar{W}^T H_2^T n_2 \end{aligned} \quad \text{Equation 9}$$

[0047] Since $\bar{W}^T H_2^T H_2 \bar{W}^*$ is a real number, the the following Equation 10 properties hold:

$$\bar{W}^T H_2^T H_2 \bar{W}^* = (\bar{W}^T H_2^T H_2 \bar{W}^*)^* = \bar{W}^H H_2^H H_2 \bar{W} \quad \text{Equation 10}$$

[0048] Equation 10 then implies the following Equation 11:

$$\begin{aligned} \bar{W}^H H_1^H r_1 + \bar{W}^T H_2^T r_2 = \\ (\bar{W}^H (H_1^H H_1 + H_2^H H_2) \bar{W}) S_1 + \bar{W}^H H_1^H n_1 + \bar{W}^T H_2^T n_2 \end{aligned} \quad \text{Equation 11}$$

Similarly, therefore:

$$\begin{aligned}
& -\bar{W}^T H_2^T r_1 + \bar{W}^H H_1^H r_2 = \\
& (\bar{W}^H (H_1^H H_1 + H_2^H H_2) \bar{W}) S_2 - \bar{W}^T H_2^T n_1 + \bar{W}^H H_1^H n_2
\end{aligned}$$

Equation 12

[0049] The signal to noise ratio for symbol S_1 is now given by Equation 13:

$$\begin{aligned}
SNR(S_1) &= \frac{(\bar{W}^H (H_1^H H_1 + H_2^H H_2) \bar{W})^2}{E[(\bar{W}^H H_1^H n_1 + \bar{W}^T H_2^T n_2)(\bar{W}^H H_1^H n_1 + \bar{W}^T H_2^T n_2)^*]} = \\
& \frac{(\bar{W}^H (H_1^H H_1 + H_2^H H_2) \bar{W})}{\sigma^2}
\end{aligned}$$

Equation 13

where $\sigma^2 = E[n_1^H n_1] = E[n_2^H n_2]$ is the variance of the noise.

[0050] Similarly the SNR for symbol S_2 is given by Equation 14:

$$SNR(S_2) = \frac{(\bar{W}^H (H_1^H H_1 + H_2^H H_2) \bar{W})}{\sigma^2}$$

Equation 14

[0051] Maximization of Equations 13 and 14 with respect to the weight vector implies the calculation of the eigen vectors for the matrix $(H_1^H H_1 + H_2^H H_2)$. Let V_1, V_2 indicate the two eigen vectors and μ_1, μ_2 be the two corresponding eigen values. User station UST picks the eigen vector with the maximum eigen value implying that:

$$\begin{aligned}
\mu_1 &> \mu_2 \Rightarrow \bar{W} = V_1 \\
\mu_2 &> \mu_1 \Rightarrow \bar{W} = V_2
\end{aligned}$$

Equation 15

[0052] User station UST then sends back the weight values W_1 and W_2 back to base station BST. Normalizing the weight $W_1 = 1$, user station UST can optionally send back only the ratio (W_2/W_1) to base station BST and base station BST then sets the weights on the antennas accordingly.

[0053] To further illustrate Equations 1 through 15 for simplicity, assume that there is only one multipath from base station BST to user station UST implying that $N = 1$. Given this assumption, then user station UST receives the following two symbols shown in Equations 16 and 17 after despreading:

$$r^1 = W_1(\alpha_1^1 S_1 - \alpha_2^1 S_2^*) + W_2(\alpha_3^1 S_1 - \alpha_4^1 S_2^*) + N_2$$

Equation 16

$$r^2 = W_1(\alpha_1^1 S_2 + \alpha_2^1 S_1^*) + W_2(\alpha_3^1 S_2 + \alpha_4^1 S_1^*) + N_1$$

Equation 17

where N_1 and N_2 are additive white Gaussian noise.

[0054] Rearranging Equations 16 and 17 yields the following Equations 18 and 19, respectively:

$$r^1 = S_1(W_1\alpha_1^1 + W_2\alpha_3^1) - S_2^*(W_1\alpha_2^1 + W_2\alpha_4^1) + N_2$$

Equation 18

$$r^2 = S_2(W_1\alpha_1^1 + W_2\alpha_3^1) + S_1^*(W_1\alpha_2^1 + W_2\alpha_4^1) + N_1$$

Equation 19

[0055] For substituting into Equations 18 and 19, and letting

$$\tilde{\alpha} = (W_1\alpha_1^1 + W_2\alpha_3^1), \tilde{\beta} = (W_1\alpha_2^1 + W_2\alpha_4^1),$$

then one skilled in the art will appreciate that Equations 18 and 19 are in the form of standard STTD implying that the total SNR for each symbol S_1 and S_2 after STTD decoding will be as shown in the following Equation 20:

$$\frac{\left| (W_1\alpha_1^1 + W_2\alpha_3^1) \right|^2 + \left| (W_1\alpha_2^1 + W_2\alpha_4^1) \right|^2}{\sigma^2} \quad \text{Equation 20}$$

[0056] Having detailed system 40, various of its advantages now may be observed. For example, system 40 achieves a $2N$ path diversity where N is the number of paths from base station BST to user station UST. As another example, versus an open loop approach alone, there is an increase of a 3 dB gain in average SNR due to the use of closed loop transmit diversity across the two antenna groups (i.e., AT1 and AT2 versus AT3 and AT4). As still another example, the required reverse link bandwidth for providing the W_1 and W_2 feedback information is that corresponding to only two antennas while system 40 is supporting four transmit antennas. As a final example, the processing operations for receiving data by user station UST may be implemented using standard STTD decoding for each of the symbols S_1 , S_2 . From each of the preceding advantages, one skilled in the art should appreciate that the preferred embodiment achieves better performance with a lesser amount of complexity than is required in a prior art approach that increases the number of transmit antennas for a given (i.e., either closed or open) diversity scheme. As yet another advantage of the preferred embodiments, while such embodiments have been described in detail, various substitutions, modifications or alterations could be made to the descriptions set forth above without departing from the inventive scope. To further appreciate this inventive flexibility, various examples of additional changes contemplated within the preferred embodiments are explored below.

[0057] While the example of system 40 has demonstrated the use of four transmit antennas, the inventive implementation of system 40 also may be applied to wireless systems with other numbers of antennas, again using a combination of open loop transmit diversity and closed loop transmit diversity as between subsets of the entire number of transmit antennas. For example, one alternative embodiment contemplated includes six transmit antennas, which for the sake of discussion let such antennas be referred to as AT10 through AT15. With this system, open loop transmit diversity may be applied to pairs of those antennas, as with a first antenna pair AT10 and AT11, a second antenna pair AT12 and AT13, and a third antenna pair AT14 and AT15. Further, closed loop transmit diversity may then be applied between each of those pairs of antennas, whereby a first weight is applied to signals transmitted by the first antenna pair, a second weight is applied to signals transmitted by the second antenna pair, and a third weight is applied to signals transmitted by the third antenna pair. As another example, a combination of open loop transmit diversity and closed loop transmit diversity may be applied to a transmitter with eight antennas. In this case, however, various additional alternatives exist. For example, the eight antennas may be split into four pairs of antennas, where open loop transmit diversity is applied within each pair of antennas, and closed loop transmit diversity is applied as between each antenna pair (i.e., four different weights, one for each antenna pair). Alternatively, the eight antennas may be split into two sets of four antennas each, where open loop transmit diversity is applied within each set of four antennas, and closed loop transmit diversity is applied as between the sets (i.e., two different weights, one for each set of four antennas).

[0058] Also while the previous examples have demonstrated more than two transmit antennas, it is recognized in connection with the present inventive aspects that a combination of open loop transmit diversity and closed loop transmit diversity may prove worthwhile for a transmitter with only two transmit antennas. Specifically, instances may arise where a transmitter in a closed loop diversity system receives feedback from a receiver to develop weights for future transmissions, but due to some factor (e.g., high Doppler) the transmitter is informed of some reduced amount of confidence in the weights; for such an application, therefore, an alternative of the preferred embodiment may be created by adding an open loop diversity technique to the closed-loop transmissions, thereby creating a combined diversity system. Figure 5 illustrates an example of such an application, and is now explored in greater detail.

[0059] Figure 5 illustrates an open and closed loop encoder 60, and which may be included within a transmitter such as transmitter 42 described above in connection with Figure 4. Encoder 60 has an input 62, which by way of example is shown to receive a first symbol S_1 at a time T followed by a second symbol S_2 at a time $2T$, and again assume by way of example that symbols S_1 and S_2 are QPSK symbols. STTD encoder 32 has two outputs 64_1 and 64_2 , each

connected to a respective antenna A60₁ and A60₂.

[0060] The operation of encoder 60 may be understood in view of the principles discussed above, and further in view of the signals shown as output to antennas A60₁ and A60₂. For example, at time T', antenna A60₁ outputs a combined signal formed by two addends, $W_3W_1S_1 + W_4S_1$, while at the same time T' antenna A60₂ outputs a combined signal formed by two addends, $W_3W_2S_1 - W_4S_2^*$. The notion of combining an open and closed loop diversity may be appreciated from these combined signals by looking at the addends in each signal; specifically, as shown below, encoder 60 operates so that for each signal transmitted it includes two addends, where the second-listed addend has a closed loop diversity and the first-listed addend has an open loop diversity. Each of the diversity types is separately discussed below.

[0061] To appreciate the open loop addends communicated by encoder 60, assume that $W_3=0$ in which case the signals communicated by antennas A60₁ and A60₂ at time T' reduce to the second-listed addends of the combined signals shown above. Specifically, for $W_3=0$, the signals output at time T' by encoder 60 reduce to an output of W_4S_1 by antenna A60₁ and an output of $-W_4S_2^*$ by antenna A60₂. By removing the common factor of W_4 from these two addends, one skilled in the art will appreciate that the remaining factors (i.e., S_1 for antenna A60₁ and $-S_2^*$ for antenna A60₂) have an open loop diversity with respect to one another. This same observation with respect to open loop diversity may be found at time 2T'. Specifically, if $W_3=0$, then the signals output at time 2T' by encoder 60 reduce to an output of W_4S_2 by antenna A60₁ and an output of $W_4S_1^*$ by antenna A60₂. By removing the common factor of W_4 from these two addends, one skilled in the art will appreciate that the remaining factors (i.e., S_2 for antenna A60₁ and S_1^* for antenna A60₂) have an open loop diversity with respect to one another.

[0062] To appreciate the closed loop addends communicated by encoder 60, assume that $W_4=0$ in which case the signals communicated by antennas A60₁ and A60₂ at time T' reduce to the first-listed addends of the combined signals shown above. Thus, for $W_4=0$, the signals output at time T' by encoder 60 reduce to an output of $W_3W_1S_1$ by antenna A60₁ and an output of $W_3W_2S_1$ by antenna A60₂. By removing the common factor of W_3 from these two addends, one skilled in the art will appreciate that the remaining factors (i.e., W_1S_1 for antenna A60₁ and W_2S_1 for antenna A60₂) have a closed loop diversity with respect to one another inasmuch as they represent a product involving the same symbol but with a different weight multiplied times each symbol. This same observation with respect to closed loop diversity may be found at time 2T'. Specifically, if $W_4=0$, then the signals output at time 2T' by encoder 60 reduce to $W_3W_1S_2$ by antenna A60₁ and an output of $W_3W_2S_2$ by antenna A60₂. Once more, by removing the common factor of W_3 from these two addends, one skilled in the art will appreciate that the remaining factors (i.e., W_1S_2 for antenna A60₁ and W_2S_2 for antenna A60₂) have an open loop diversity with respect to one another.

[0063] Concluding the discussion of Figure 5, it may be observed that encoder 60 again supports a transmitter with two sets of transmit antennas, where in this case each set consists of a single antenna rather than multiple antennas as in the previously-described embodiments. Nonetheless, the transmitter receives feedback from its receiver in order to implement closed loop diversity by applying different weights to some of the symbols to form signals for communication by the transmitter (via its encoder) while other of the signals communicated by the transmitter result from symbols selectively modified according to an open loop diversity technique.

[0064] As still another example of the present inventive scope, the types of open loop and closed loop transmit diversity also may be changed as applied to the preferred embodiments. Thus, while TxAA has been shown above as a closed loop technique, and STTD has been shown as an open loop technique, one or both of these may be replaced by corresponding alternative techniques and applied to a multiple transmit antenna system, thereby again providing a combined closed loop and open loop transmit antenna system. Indeed, recall above an example is set forth for an inventive system having eight antennas split into sets of four antennas, where open loop transmit diversity is applied within each set of four antennas. In this case, the application of open loop transmit diversity as applied within a set of four antennas will require a type of open loop diversity other than solely the transmission of conjugates; in other words, a use only of conjugates provides two different signals, whereas for four different antennas a corresponding four different signals are required to achieve the open loop diversity. Accordingly, for this as well as other embodiments, a different open loop diversity approach may be implemented. For example, another open loop diversity technique that may be implemented according to the preferred embodiment includes orthogonal transmit diversity ("OTD"), and which is shown for a single OTD encoder 70 in Figure 6 and for BPSK symbols. In Figure 6, OTD encoder 70 is coupled to transmit symbols to four antennas A70₁ through A70₄. Further, in operation, OTD encoder 70 buffers a number of symbols equal to its number of antennas (i.e., four in the example of Figure 6), and then each antenna transmits only one corresponding symbol and that is in a form that is orthogonal to all other symbols transmitted along the other antennas. These forms are shown by way of the output symbols in Figure 6 along antennas A70₁ through A70₄ from time T' through time 4T'. Further, for simplicity Figure 6 only illustrates the OTD operation and, thus, does not further show the use of weighting to achieve the combined closed loop diversity. Nonetheless, the addition of a closed loop weighting operation should be readily implemented by one skilled in the art given the preceding teachings with respect to other embodiments. As another example of an alternative open loop diversity that may be used according to the preferred embodiments, Figure 7 illustrates an STTD encoder 80 for four antennas A80₁ through A80₄. The conventions

of Figure 7 should be readily appreciated from the preceding examples, where the signals transmitted along antennas A80₁ through A80 therefore represent open loop diverse signals, and for the example where the symbols are BPSK symbols. Also as in the case of Figure 6, for simplicity Figure 7 only illustrates the open loop diversity operation (i.e., STTD) and, thus, Figure 7 does not further show the use of weighting to achieve the combined closed loop diversity, where such additional weighting may be implemented by one skilled in the art according to the teachings of this document. As still another example of an alternative open loop diversity that may be used according to the preferred embodiments, Figure 8 illustrates time switched time diversity ("TSTD") for four antennas. Lastly, other closed loop diversity techniques that may be used to create still further alternative embodiments include switched diversity.

[0065] As still another example of the inventive scope, note that various of such teachings may be applied to other wireless systems. For example, the preceding may be applied to systems complying with the 3rd Generation partnership Project ("3GPP") for wireless communications, and to 3GPP 2 systems, as well as still other standardized or non-standardized systems. Further, while the preceding example has been shown in a CDMA system (or a WCDMA system), the preferred embodiment may be implemented by including transmitter antenna diversity combining both open loop and closed loop diversity in a time division multiple access ("TDMA") system, which has a spreading gain of one.

[0066] As a final example of the inventive scope, while the preceding embodiments have been shown in connection with a receiver having only a single antenna, note that systems using multiple receive antennas also are contemplated. In other words, therefore, the preceding also may be combined with various techniques of receive antenna diversity.

[0067] From the preceding, one skilled in the art should appreciate various aspects of the inventive scope, as is defined by the following claims.

Claims

1. A wireless communication system, comprising:

transmitter circuitry comprising encoder circuitry for receiving a plurality of symbols;
a plurality of antennas coupled to the transmitter circuitry and for transmitting signals from the transmitter circuitry to a receiver, wherein the signals are responsive to the plurality of symbols; and
wherein the encoder circuitry is for applying open loop diversity and closed loop diversity to the plurality of symbols to form the signals.

2. The system of claim 1:

wherein the plurality of antennas comprises a plurality of sets of antennas; and
wherein for each of the sets of antennas the encoder circuitry is for applying open loop diversity to selected ones of the plurality of symbols such that signals transmitted by any one antenna in the set of antennas represent open loop diversity with respect to signals transmitted by any other antenna in the set of antennas.

3. The system of claim 2 wherein for each of the sets of antennas the encoder circuitry is for applying a weight to the plurality of symbols such that signals transmitted in response to the weight represent a closed loop diversity with respect to signals transmitted by any other antenna in any other of the sets of antennas.

4. The system of claim 3:

wherein the plurality of sets of antennas consists of two sets of antennas; and
wherein each of the sets of antennas consists of two antennas.

5. The system of claim 3:

wherein the plurality of sets of antennas consists of three sets of antennas; and
wherein each of the sets of antennas consists of two antennas.

6. The system of claim 3:

wherein the plurality of sets of antennas consists of two sets of antennas; and
wherein each of the sets of antennas consists of four antennas.

7. The system of claim 3:

wherein the plurality of sets of antennas consists of four sets of antennas; and
wherein each of the sets of antennas consists of two antennas.

- 5 8. The system of any one of claims 1 to 7, wherein the open loop diversity comprises space time block coded transmit antenna diversity.
- 10 9. The system of any one of claims 1 to 7, wherein the open loop diversity comprises orthogonal transmit diversity.
- 10 10. The system of any one of claims 1 to 7, wherein the open loop diversity comprises time switched time diversity.
- 10 11. The system of any one of claims 1 to 7, wherein the closed loop diversity comprises transmit adaptive array diversity.
- 15 12. The system of claim 11 wherein the open loop diversity comprises space time block coded transmit antenna diversity.
- 15 13. The system of claim 1 and further comprising a receiver.
- 20 14. The system of claim 13 wherein the receiver comprises one antenna for receiving the signals transmitted from the plurality of antennas.
- 20 15. The system of claim 13 wherein the receiver comprises a plurality of antennas, wherein each of the plurality of antennas is for receiving the signals transmitted from the plurality of antennas.
- 25 16. The system of any one of claims 13 to 15, wherein the receiver comprises decoder circuitry for decoding open loop diversity and closed loop diversity with respect to the plurality of symbols.
- 25 17. The system of claim 16 wherein the receiver further comprises:
- 30 a despreader having an output and for producing a despread symbol stream at the output in response to the signals, wherein the output is coupled to the decoder circuitry;
- 30 a channel estimator coupled to the output of the despreader and for determining estimated channel impulse responses based on the despread symbol stream; and
- 30 wherein the decoder circuitry is for decoding open loop diversity and closed loop diversity with respect to the despread symbol stream and in response to the estimated channel impulse responses.
- 35 18. The system of claim 16 or claim 17, wherein the receiver further comprises a deinterleaver coupled to an output of the decoder circuitry and for providing an inverse interleaving function with respect to information received from the decoder circuitry.
- 40 19. The system of claim 18 wherein the receiver further comprises a channel decoder coupled to an output of the deinterleaver and for improving a data error rate of information received from the deinterleaver.
- 45 20. The system of any one of claims 1 to 19, wherein the signals comprise CDMA communications.
- 45 21. The system of any one of claims 1 to 19, wherein the signals comprise WCDMA communications.
- 45 22. The system of any one of claims 1 to 19, wherein the signals comprise TDMA communications.
- 50 23. The system of any one of claims 1 to 22,
- 50 wherein the transmitter circuitry is located in a base station and
- 50 wherein a receiver comprises a mobile receiver.
- 55 24. The system of any one of claims 1 to 23, wherein the plurality of symbols comprise quadrature phase shift keying symbols.
- 55 25. The system of any one of claims 1 to 23, wherein the plurality of symbols comprise binary phase shift keying symbols.

EP 1 073 212 A2

26. The system of any one of claims 1 to 23, wherein the plurality of symbols comprise quadrature amplitude modulation symbols.

27. The system of any one of claims 1 to 26, wherein the transmitter circuitry further comprises:

a channel encoder for receiving a plurality of bits;
an interleaver coupled to an output of the channel encoder and for shuffling a block of encoded bits; and
a symbol mapper coupled to an output of the interleaver for converting shuffled bits into the plurality of symbols.

28. A wireless communication receiver for receiving signals from transmitter circuitry transmitting along a plurality of transmit antennas, wherein the signals are formed by the transmitter circuitry by applying open loop diversity and closed loop diversity to a plurality of symbols, the receiver comprising:

a despreaders having an output and for producing a despread symbol stream at the output in response to the signals; and
decoder circuitry coupled to the output of the despreaders and for decoding open loop diversity and closed loop diversity with respect to the despread symbol stream.

29. The receiver of claim 28 and further comprising one antenna for receiving the signals transmitted from the plurality of transmit antennas.

30. The receiver of claim 28 and further comprising a plurality of antennas for receiving the signals transmitted from the plurality of transmit antennas.

31. The receiver of any one of claims 28 to 30, further comprising:

a channel estimator coupled to the output of the despreaders and for determining estimated channel impulse responses based on the despread symbol stream; and
wherein the decoder circuitry is for decoding open loop diversity and closed loop diversity with respect to the despread symbol stream and in response to the estimated channel impulse responses.

32. The receiver of claim 31 and further comprising a deinterleaver coupled to an output of the decoder circuitry and for providing an inverse interleaving function with respect to information received from the decoder circuitry.

33. The system of claim 32 and further comprising a channel decoder coupled to an output of the deinterleaver and for improving a data error rate of information received from the deinterleaver.



34. A method of operating a wireless communication system, comprising the steps of:



receiving a plurality of symbols into encoder circuitry;
applying open loop diversity and closed loop diversity to the plurality of symbols to form a plurality of signals;
and
transmitting the plurality of signals along a plurality of antennas to a receiver.

35. The method of claim 34:

wherein the plurality of antennas comprises a plurality of sets of antennas; and
wherein the step of applying open loop diversity and closed loop diversity applies open loop diversity to selected ones of the plurality of symbols such that signals transmitted by any one antenna in the set of antennas represent open loop diversity with respect to signals transmitted by any other antenna in the set of antennas.

36. The method of claim 35 wherein for each of the sets of antennas the step of applying open loop diversity and closed loop diversity applies a weight to the plurality of symbols such that signals transmitted in response to the weight represent a closed loop diversity with respect to signals transmitted by any other antenna in any other of the sets of antennas.








FIG. 5




FIG. 6




FIG. 7




FIG. 8

(19)



Europäisches Patentamt

European Patent Office

Office européen des brevets



(11)

EP 1 073 212 A3

(12)

EUROPEAN PATENT APPLICATION

(88) Date of publication A3:
22.10.2003 Bulletin 2003/43

(51) Int Cl.7: H04B 7/06, H04L 1/06

(43) Date of publication A2:
31.01.2001 Bulletin 2001/05

(21) Application number: 00304512.7

(22) Date of filing: 26.05.2000

(84) Designated Contracting States:
AT BE CH CY DE DK ES FI FR GB GR IE IT LI LU
MC NL PT SE
Designated Extension States:
AL LT LV MK RO SI

(72) Inventors:

- Dabak, Anand G.
Plano, Texas 75025 (US)
- Hosur, Srinath
Plano, Texas 75025 (US)

(30) Priority: 28.05.1999 US 136413 P

(74) Representative:

Legg, Cyrus James Grahame et al
ABEL & IMRAY,
20 Red Lion Street
London WC1R 4PQ (GB)

(71) Applicant: Texas Instruments Incorporated
Dallas, Texas 75251 (US)

(54) Wireless system with transmitter with multiple antennas and combining open loop and closed loop transmit diversity

(57) A wireless communication system (40). The system comprises transmitter circuitry (42) comprising encoder circuitry (44) for receiving a plurality of symbols (S_i). The system further comprises a plurality of antennas (AT1-AT4) coupled to the transmitter circuitry and

for transmitting signals from the transmitter circuitry to a receiver (UST), wherein the signals are responsive to the plurality of symbols. Further, the encoder circuitry is for applying open loop diversity and closed loop diversity to the plurality of symbols to form the signals.




FIG. 4



European Patent
Office

EUROPEAN SEARCH REPORT

Application Number
EP 00 30 4512

DOCUMENTS CONSIDERED TO BE RELEVANT			
Category	Citation of document with indication, where appropriate, of relevant passages	Relevant to claim	CLASSIFICATION OF THE APPLICATION (InCL.7)
A	ALAMOUTI S M: "A simple transmit diversity technique for wireless communications" IEEE JOURNAL ON SELECTED AREAS IN COMMUNICATIONS, IEEE INC. NEW YORK, US, vol. 16, no. 8, October 1998 (1998-10), pages 1451-1458, XP002100058 ISSN: 0733-8716 * page 1452, line 32 - line 43 *	1,28	H04B7/06 H04L1/06
A	ROHANI K ET AL: "A comparison of base station transmit diversity methods for third generation cellular standards" VEHICULAR TECHNOLOGY CONFERENCE, 1999 IEEE 49TH HOUSTON, TX, USA 16-20 MAY 1999, PISCATAWAY, NJ, USA, IEEE, US, 16 May 1999 (1999-05-16), pages 351-355, XP010341997 ISBN: 0-7803-5565-2 * abstract *	1,28	
A	HEATH R W JR ET AL: "A simple scheme for transmit diversity using partial channel feedback" SIGNALS, SYSTEMS & COMPUTERS, 1998. CONFERENCE RECORD OF THE THIRTY-SECOND ASIOMAR CONFERENCE ON PACIFIC GROVE, CA, USA 1-4 NOV. 1998, PISCATAWAY, NJ, USA, IEEE, US, 1 November 1998 (1998-11-01), pages 1073-1078, XP010324515 ISBN: 0-7803-5148-7 * 1. Introduction * * page 1074, line 40 - page 1075, line 7 *	1,28	TECHNICAL FIELDS SEARCHED (InCL.7) H04B H04L
The present search report has been drawn up for all claims			
Place of search MUNICH		Date of completion of the search 8 August 2003	Examiner LOPEZ DE ECHAZA..., G
CATEGORY OF CITED DOCUMENTS X : particularly relevant if taken alone Y : particularly relevant if combined with another document of the same category A : technological background O : non-written disclosure P : intermediate document		T : theory or principle underlying the invention E : earlier patent document, but published on, or after the filing date D : document cited in the application L : document cited for other reasons & : member of the same patent family, corresponding document	

EPO FORM 1503 03.82 (P04C01)